

Cleaning and Disinfecting HME Drive-Thru Headset Surfaces (HS6000, HS6100, HS6200, HS6300, HS12, BP6000, BP6100 and BP6200)

To further minimize the risk of passing germs, infections, and bacteria from one user to the other.

Time Required:

5 minutes to prepare, 5 minutes to complete.

Tools and Supplies:

Sanitizer-soaked towel KAY Peroxide Multi Surface Disinfectant & Cleaner (MSDC).

Step 1:

- Turn off the headset and remove the battery.

Step 2:

- Remove foam earpad.
- Verify that all headsets have microphone windscreens and foam earpads in good condition.
- Replace microphone windscreens and foam earpads as needed.
- While not intended as a solely single use item, the condition of each microphone windscreen should be monitored.

Step 3:

- Clean foam earpad pieces with warm soapy water, then spray foam piece with MSDC.
- Let foam pieces air dry.

Step 4:

- Wipe clean the entire headset surface and battery unit.
- Spray MSDC into a lightly dampened clean sanitizer-soaked bar towel.
- Take extra care and diligence when wiping mouthpiece.
- Allow to air dry before next use.

NOTE:

Never spray cleaner directly onto the headset. Cleaner must be sprayed onto a bar towel first.

Step 5:

- Immediately place used bar towel into a soiled towel bucket.



For replacement foam earpads or microphone windscreens, contact **HME: 800-848-4468 — Option 1, 1, 1**

In the US and Canada, Call 800-848-4468 or your local authorized HME dealer
All other countries, contact your local authorized HME distributor for more information

HM Electronics, Inc. 2848 Whiptail Loop, Carlsbad, CA 92010 | USA | www.hme.com/qsr | Tel: (800) 848.4468

© 2020 HM Electronics, Inc. The HME logo and product names are registered trademarks of HM Electronics, Inc. LT20-03.